

Enter the text guide

Menu + >> + >> + “PREFIXES”

End a call or an operation

Use loudspeaker and hands-free modes

Make a call without using the handset Dial without

Answer a call without using the handset Select Lx key flashing

Switch to hands-free +

Activate/deactivate loudspeaker

Activate/deactivate mute Pre-programmed headset mode Mute + * + 1 simultaneously + L3 (LED on)

Headset/handset (or R8 for version

Call

By name (from key panel) Name + enter first letter of the name + select the softkey when name is displayed

Attendant 9

External number 0 + external number

Abbreviated number 2 + abbreviated number

Redial last external Nr dialled “REDIAL”

Using repertory key associated to person you want to call

Avoiding receiving bips or intrusion >> “PROTECT” + number you want to call

Sign-on / sign-off

>> “SIGN-ON” + your extension number + password + + Nb you want to call “AUTOMATIC CALLBACK” +

Automatic call-back

Intrusion

Voice message

Voice message to a group “INTRUSION” “VOICE PAGING” Dial number of the group

Answer a call

Call pick-up “PICKUP”+ number of ringing extension

Call pick-up in a group “PICKUP”+ “GROUP”

General ringing call pick-up “PICKUP”+ “GENERAL”

Opening the doorphone >> + “DOOR LOCK”

During a communication

Adjust volume of speakerphone

Identify another incoming call Menu + flashing key

On hold flashing key

Answer a new call flashing key

Broker’s call

Conference flashing key Call a 2nd person + “CONFER”

Transfer a call to another extension Dial extension Nr +

Call park “CALL PARK”+ 2 digits code at your choice +

Retrieve a parked call “RETRIEVE”+ chosen 2-digit code

Messages and callers file

Send a text message on not answering extension >> + “MSG” + “DISC” + “SELECT” or “NEXT” + complete the message + “CONFIRM”

Read the callers file “CALLERS”

Call forwarding

Immediate call forwarding

ACTIVATION	DEACTIVATION
Menu + “CALL FWD” + choose type of call fwd + call fwd Nb + “CONFIRM”	Call fwd

Remote call forwarding

Menu + “CALL FWD” + “REMOTE FWD” + yr extension Nr + choose type of call fwd + call fwd Nb + password	Call fwd (from your set)
---	--------------------------

Program a registered call forwarding

Menu + >> + “FIXED FWD” + choose type of call fwd + call fwd Nb + “CONFIRM”	Program another registered call forwarding
--	--

Activate call forwarding

Call fwd	Call fwd
----------	----------

Programming your terminal**Reminder****ACTIVATION**

7 1 + HHMM
4 digits - time of the reminder

Program dedicated repertory keys on line keys

☒ Menu

+ ☒ >>

+“DIRECTORY”+
press key to register
+ Nr to register
+ “CONFIRM”
+ ☒

Change password

7 9 + old password
+ new password

Lock your phone

☒ Menu

+ “LOCK”

Retrieve from « all-calls » group

☒ Menu

“GROUP”

Temporary operator

☒ Menu

“GEN CALL”

Choose ringing melody & adjust loudspeaker volume

☒ Menu

+“RING-SPKR”

Change voice paging mode

(bi-directional mode)

☒ Menu + ☒ >>

+ “V.PAGING”

+“MODIFY” + ☒

DEACTIVATION

7 1 + **9**

☒ Menu

+ ☒ >>

+“DIRECTORY”
press key to register
“BLANK”
“CONFIRM”
+ ☒

☒ Menu

+ “LOCK”

☒ Menu

“GROUP”

☒ Menu

“GEN CALL”

Attendant facilities**Attendant console activation**

☒ Menu + “GEN-CALL”

Attendant console deactivation / programming of extra night set

☒ Menu + “GEN-CALL” +

extra night set Nr + ☒

or “CONFIRM” or “MODIFY”
or “NONIGHTST”

Override of “do not disturb”**System call forwarding****Deactivate system call forwarding****Call forwarding for a third party****Programming date and time****Programming abbreviated number****Initialisation of pass word for an extension****Hotel facilities****“OVERRIDE”**

☒ Menu + “CALL-FWD”

+ ☒ >> “SYSTEM”+ external number (without 0)

☒ Menu + “CALL-FWD”

+ ☒ >> “CANC-SYST”

☒ Menu + “CALL-FWD”

+ ☒ >> “REMOTE FWD”

+ number to forward + call forwarding type + forwarding Nr

☒ Menu + ☒ >>

+“SYSTEM”+ “DATE”+ figures
“CONFIRM”

☒ Menu + ☒ >>

+“SYSTEM”+ “ABBR-NR”+ Nr of list + short number + complete number + “CONFIRM”

☒ Menu + ☒ >>

+“SYSTEM”+ 1234 + ☒ >>

+“PASSWORD”+ + extension Nr
See user guide for hotel console



MD Evolution System Telephone

DIALOG 4223 Professional

Declaration of Conformity

Hereby, Aastra Telecom Sweden AB, SE-126 37 Hägersten, declares that this telephone is in conformity with the essential requirements and other relevant provisions of the R&TTE directive 1999/5/EC.

Details to be found at: <http://www.aastra.com/sdoc>



For questions regarding the product, please contact your Aastra Certified Sales Partner. Also visit us on: www.aastra.com

Subject to alteration without notice

© Aastra Telecom Sweden AB 2008. All rights reserved.
EN/LZTBS 102 1937 R3A